

TMS320F2802x, 2803x Piccolo Enhanced Capture (eCAP) Module

Reference Guide



Literature Number: SPRUFZ8A
May 2009–Revised October 2009

Preface	6
1 Introduction	8
2 Description	8
3 Capture and APWM Operating Mode	9
4 Capture Mode Description	10
4.1 Event Prescaler	10
4.2 Edge Polarity Select and Qualifier	11
4.3 Continuous/One-Shot Control	11
4.4 32-Bit Counter and Phase Control	12
4.5 CAP1-CAP4 Registers	13
4.6 Interrupt Control	13
4.7 Shadow Load and Lockout Control	14
4.8 APWM Mode Operation	15
5 Capture Module - Control and Status Registers	16
6 Register Mapping	24
7 Application of the ECAP Module	24
7.1 Example 1 - Absolute Time-Stamp Operation Rising Edge Trigger	25
7.2 Example 2 - Absolute Time-Stamp Operation Rising and Falling Edge Trigger	27
7.3 Example 3 - Time Difference (Delta) Operation Rising Edge Trigger	29
7.4 Example 4 - Time Difference (Delta) Operation Rising and Falling Edge Trigger	31
8 Application of the APWM Mode	33
8.1 Example 1 - Simple PWM Generation (Independent Channel/s)	33
Appendix A Revision History	34

List of Figures

1	Capture and APWM Modes of Operation	9
2	Capture Function Diagram	10
3	Event Prescale Control	11
4	Prescale Function Waveforms	11
5	Details of the Continuous/One-shot Block	12
6	Details of the Counter and Synchronization Block	13
7	Interrupts in eCAP Module	14
8	PWM Waveform Details Of APWM Mode Operation	15
9	Time-Stamp Counter Register (TSCTR)	16
10	Counter Phase Control Register (CTRPHS)	16
11	Capture-1 Register (CAP1)	16
12	Capture-2 Register (CAP2)	16
13	Capture-3 Register (CAP3)	17
14	Capture-4 Register (CAP4)	17
15	ECAP Control Register 1 (ECCTL1)	17
16	ECAP Control Register 2 (ECCTL2)	18
17	ECAP Interrupt Enable Register (ECEINT)	21
18	ECAP Interrupt Flag Register (ECFLG)	22
19	ECAP Interrupt Clear Register (ECCLR)	22
20	ECAP Interrupt Forcing Register (ECFRC)	23
21	Capture Sequence for Absolute Time-stamp and Rising Edge Detect	25
22	Capture Sequence for Absolute Time-stamp With Rising and Falling Edge Detect	27
23	Capture Sequence for Delta Mode Time-stamp and Rising Edge Detect	29
24	Capture Sequence for Delta Mode Time-stamp With Rising and Falling Edge Detect	31
25	PWM Waveform Details of APWM Mode Operation	33

List of Tables

1	Time-Stamp Counter Register (TSCTR) Field Descriptions	16
2	Counter Phase Control Register (CTRPHS) Field Descriptions.....	16
3	Capture-1 Register (CAP1) Field Descriptions	16
4	Capture-2 Register (CAP2) Field Descriptions	16
5	Capture-3 Register (CAP3) Field Descriptions	17
6	Capture-4 Register (CAP4) Field Descriptions	17
7	ECAP Control Register 1 (ECCTL1) Field Descriptions.....	17
8	ECAP Control Register 2 (ECCTL2) Field Descriptions.....	19
9	ECAP Interrupt Enable Register (ECEINT) Field Descriptions	21
10	ECAP Interrupt Flag Register (ECFLG) Field Descriptions	22
11	ECAP Interrupt Clear Register (ECCLR) Field Descriptions	23
12	ECAP Interrupt Forcing Register (ECFRC) Field Descriptions	23
13	Control and Status Register Set.....	24
14	Changes Made in This Revision.....	34

Read This First

The enhanced capture (eCAP) module is used in systems where accurate timing of external events is important. This guide describes the TMS320x2802x, 2803x Piccolo™ Enhanced Capture (eCAP) Module module and how to use it.

The eCAP module described in this reference guide is a Type 0 eCAP. See the *TMS320C28xx, 28xxx DSP Peripheral Reference Guide* ([SPRU566](#)) for a list of all devices with a eCAP module of the same type, to determine the differences between the types, and for a list of device-specific differences within a type.

Related Documentation From Texas Instruments

The following documents describe the TMS320C2802x, 2803x Piccolo™ devices and related support tools and can be downloaded from the TI website (www.ti.com):

Data Manuals—

[SPRS523](#) — **TMS320F28020, TMS320F28021, TMS320F28022, TMS320F28023, TMS320F28026, TMS320F28027 Piccolo Microcontrollers Data Manual** contains the pinout, signal descriptions, as well as electrical and timing specifications for the 2802x devices.

[SPRZ292](#) — **TMS320F28020, TMS320F28021, TMS320F28022, TMS320F28023, TMS320F28026, TMS320F28027 Piccolo MCU Silicon Errata** describes known advisories on silicon and provides workarounds.

[SPRS584](#) — **TMS320F28032, TMS320F28033, TMS320F28034, TMS320F28035 Piccolo Microcontrollers Data Manual** contains the pinout, signal descriptions, as well as electrical and timing specifications for the 2803x devices.

[SPRZ295](#) — **TMS320F28032, TMS320F28033, TMS320F28034, TMS320F28035 Piccolo MCU Silicon Errata** describes known advisories on silicon and provides workarounds.

CPU User's Guides—

[SPRU430](#) — **TMS320C28x CPU and Instruction Set Reference Guide** describes the central processing unit (CPU) and the assembly language instructions of the TMS320C28x fixed-point digital signal processors (DSPs). It also describes emulation features available on these DSPs.

Peripheral Guides—

[SPRUFN3](#) — **TMS320x2802x Piccolo System Control and Interrupts Reference Guide** describes the various interrupts and system control features of the 2802x microcontrollers (MCUs).

[SPRUGL8](#) — **TMS320x2803x Piccolo System Control and Interrupts Reference Guide** describes the various interrupts and system control features of the 2803x microcontrollers (MCUs).

[SPRU566](#) — **TMS320x28xx, 28xxx DSP Peripheral Reference Guide** describes the peripheral reference guides of the 28x digital signal processors (DSPs).

[SPRUG00](#) — **TMS320x2803x Piccolo Boot ROM Reference Guide** describes the purpose and features of the bootloader (factory-programmed boot-loading software) and provides examples of code. It also describes other contents of the device on-chip boot ROM and identifies where all of the information is located within that memory.

- [SPRUFN6](#) — TMS320x2802x Piccolo Boot ROM Reference Guide** describes the purpose and features of the bootloader (factory-programmed boot-loading software) and provides examples of code. It also describes other contents of the device on-chip boot ROM and identifies where all of the information is located within that memory.
- [SPRUGE6](#) — TMS320x2803x Piccolo Control Law Accelerator (CLA) Reference Guide** describes the operation of the Control Law Accelerator (CLA).
- [SPRUGE2](#) — TMS320x2803x Piccolo Local Interconnect Network (LIN) Module Reference Guide** describes the operation of the Local Interconnect Network (LIN) Module.
- [SPRUFK8](#) — TMS320x2803x Piccolo Enhanced Quadrature Encoder Pulse (eQEP) Reference Guide** describes the operation of the Enhanced Quadrature Encoder Pulse (eQEP) module, which is used for interfacing with a linear or rotary incremental encoder to get position, direction, and speed information from a rotating machine in high performance motion and position control systems. It includes the module description on registers.
- [SPRUGL7](#) — TMS320x2803x Piccolo Enhanced Controller Area Network (eCAN) Reference Guide** describes the operation of the Enhanced Controller Area Network (eCAN) which uses established protocol to communicate serially with other controllers in electrically noisy environments.
- [SPRUGE5](#) — TMS320x2802x, 2803x Piccolo Analog-to-Digital Converter (ADC) and Comparator Reference Guide** describes how to configure and use the on-chip ADC module, which is a 12-bit pipelined ADC.
- [SPRUGE9](#) — TMS320x2802x, 2803x Piccolo Enhanced Pulse Width Modulator (ePWM) Module Reference Guide** describes the main areas of the enhanced pulse width modulator that include digital motor control, switch mode power supply control, UPS (uninterruptible power supplies), and other forms of power conversion.
- [SPRUGE8](#) — TMS320x2802x, 2803x Piccolo High-Resolution Pulse Width Modulator (HRPWM)** describes the operation of the high-resolution extension to the pulse width modulator (HRPWM).
- [SPRUGH1](#) — TMS320x2802x, 2803x Piccolo Serial Communications Interface (SCI) Reference Guide** describes how to use the SCI.
- [SPRUFZ8](#) — TMS320x2802x, 2803x Piccolo Enhanced Capture (eCAP) Module Reference Guide** describes the enhanced capture module. It includes the module description and registers.
- [SPRUG71](#) — TMS320x2802x, 2803x Piccolo Serial Peripheral Interface (SPI) Reference Guide** describes the SPI - a high-speed synchronous serial input/output (I/O) port - that allows a serial bit stream of programmed length (one to sixteen bits) to be shifted into and out of the device at a programmed bit-transfer rate.
- [SPRUFZ9](#) — TMS320x2802x, 2803x Piccolo Inter-Integrated Circuit (I2C) Reference Guide** describes the features and operation of the inter-integrated circuit (I2C) module.

Tools Guides—

- [SPRU513](#) — TMS320C28x Assembly Language Tools v5.0.0 User's Guide** describes the assembly language tools (assembler and other tools used to develop assembly language code), assembler directives, macros, common object file format, and symbolic debugging directives for the TMS320C28x device.
- [SPRU514](#) — TMS320C28x Optimizing C/C++ Compiler v5.0.0 User's Guide** describes the TMS320C28x™ C/C++ compiler. This compiler accepts ANSI standard C/C++ source code and produces TMS320 DSP assembly language source code for the TMS320C28x device.
- [SPRU608](#) — TMS320C28x Instruction Set Simulator Technical Overview** describes the simulator, available within the Code Composer Studio for TMS320C2000 IDE, that simulates the instruction set of the C28x™ core.

Enhanced Capture (eCAP) Module

The enhanced Capture (eCAP) module is essential in systems where accurate timing of external events is important.

This reference guide is applicable for the eCAP found on the TMS320x2802x, 2803x Piccolo™ family of processors. This includes all Flash-based, ROM-based, and RAM-based devices within the 2834x family .

1 Introduction

Uses for eCAP include:

- Speed measurements of rotating machinery (e.g., toothed sprockets sensed via Hall sensors)
- Elapsed time measurements between position sensor pulses
- Period and duty cycle measurements of pulse train signals
- Decoding current or voltage amplitude derived from duty cycle encoded current/voltage sensors

The eCAP module described in this guide includes the following features:

- 4-event time-stamp registers (each 32 bits)
- Edge polarity selection for up to four sequenced time-stamp capture events
- Interrupt on either of the four events
- Single shot capture of up to four event time-stamps
- Continuous mode capture of time-stamps in a four-deep circular buffer
- Absolute time-stamp capture
- Difference (Delta) mode time-stamp capture
- All above resources dedicated to a single input pin
- When not used in capture mode, the ECAP module can be configured as a single channel PWM output

2 Description


The eCAP module represents one complete capture channel that can be instantiated multiple times depending on the target device. In the context of this guide, one eCAP channel has the following independent key resources:

- Dedicated input capture pin
- 32-bit time base (counter)
- 4 x 32-bit time-stamp capture registers (CAP1-CAP4)
- 4-stage sequencer (Modulo4 counter) that is synchronized to external events, ECAP pin rising/falling edges.
- Independent edge polarity (rising/falling edge) selection for all 4 events
- Input capture signal prescaling (from 2-62)
- One-shot compare register (2 bits) to freeze captures after 1 to 4 time-stamp events
- Control for continuous time-stamp captures using a 4-deep circular buffer (CAP1-CAP4) scheme
- Interrupt capabilities on any of the 4 capture events

3 Capture and APWM Operating Mode

You can use the eCAP module resources to implement a single-channel PWM generator (with 32 bit capabilities) when it is not being used for input captures. The counter operates in count-up mode, providing a time-base for asymmetrical pulse width modulation (PWM) waveforms. The CAP1 and CAP2 registers become the active period and compare registers, respectively, while CAP3 and CAP4 registers become the period and capture shadow registers, respectively. Figure 1 is a high-level view of both the capture and auxiliary pulse-width modulator (APWM) modes of operation.

Figure 1. Capture and APWM Modes of Operation




- A A single pin is shared between CAP and APWM functions. In capture mode, it is an input; in APWM mode, it is an output.
- B In APWM mode, writing any value to CAP1/CAP2 active registers also writes the same value to the corresponding shadow registers CAP3/CAP4. This emulates immediate mode. Writing to the shadow registers CAP3/CAP4 invokes the shadow mode.

4 Capture Mode Description

Figure 2 shows the various components that implement the capture function.


Figure 2. Capture Function Diagram




4.1 Event Prescaler

- An input capture signal (pulse train) can be prescaled by $N = 2-62$ (in multiples of 2) or can bypass the prescaler.

This is useful when very high frequency signals are used as inputs. Figure 3 shows a functional diagram and Figure 4 shows the operation of the prescale function.

Figure 3. Event Prescale Control


- A When a prescale value of 1 is chosen (i.e. ECCTL1[13:9] = 0,0,0,0,0) the input capture signal by-passes the prescale logic completely.

Figure 4. Prescale Function Waveforms


4.2 Edge Polarity Select and Qualifier

- Four independent edge polarity (rising edge/falling edge) selection MUXes are used, one for each capture event.
- Each edge (up to 4) is event qualified by the Modulo4 sequencer.
- The edge event is gated to its respective CAPx register by the Mod4 counter. The CAPx register is loaded on the falling edge.

4.3 Continuous/One-Shot Control


- The Mod4 (2 bit) counter is incremented via edge qualified events (CEVT1-CEVT4).
- The Mod4 counter continues counting (0->1->2->3->0) and wraps around unless stopped.
- A 2-bit stop register is used to compare the Mod4 counter output, and when equal stops the Mod4 counter and inhibits further loads of the CAP1-CAP4 registers. This occurs during one-shot operation.

In continuous mode, the Mod4 counter continues to run (0->1->2->3->0, the one-shot action is ignored, and capture values continue to be written to CAP1-4 in a circular buffer sequence.

The diagram illustrates the internal logic of the ECCTL2 module. At the bottom, two input registers are shown: `ECCTL2[STOP_WRAP]` and `ECCTL2[RE-ARM]` / `ECCTL2[CONT/ONESHT]`. The `ECCTL2[STOP_WRAP]` register feeds into a `Stop value (2b)` block. The `ECCTL2[RE-ARM]` / `ECCTL2[CONT/ONESHT]` register feeds into a `One-shot control logic` block. The `Stop value (2b)` block's output is compared with the output of a `Modulo 4 counter` (labeled `Mod_eq`) using an equality comparator. The `Modulo 4 counter` is clocked by `CLK` (from `CEVT1`), has a `Stop` input (from `CEVT2`), and a `RST` input (from `CEVT3`). The `One-shot control logic` block has inputs from `CEVT2` and `CEVT3`, and its output is connected to the `Stop` input of the `Modulo 4 counter`. The output of the equality comparator is connected to the `2` input of the `2:4 MUX`. The `2:4 MUX` also receives inputs from `0`, `1`, `2`, and `3` (from `CEVT1`, `CEVT2`, `CEVT3`, and `CEVT4` respectively). The output of the `2:4 MUX` is the final output of the module.

On any of the four event loads, an option to reset the 32-bit counter is given. This is useful for time difference capture. The 32-bit counter value is captured first, then it is reset to 0 by any of the LD1-LD4 signals.

Figure 6. Details of the Counter and Synchronization Block



4.5 CAP1-CAP4 Registers

These 32-bit registers are fed by the 32-bit counter timer bus, CTR[0-31] and are loaded (i.e., capture a time-stamp) when their respective LD inputs are strobed.

Loading of the capture registers can be inhibited via control bit CAPLDEN. During one-shot operation, this bit is cleared (loading is inhibited) automatically when a stop condition occurs, i.e. StopValue = Mod4.

CAP1 and CAP2 registers become the active period and compare registers, respectively, in APWM mode.

CAP3 and CAP4 registers become the respective shadow registers (APRD and ACMP) for CAP1 and CAP2 during APWM operation.

4.6 Interrupt Control

An Interrupt can be generated on capture events (CEVT1-CEVT4, CTROVF) or APWM events (CTR = PRD, CTR = CMP).

A counter overflow event (FFFFFFFF->00000000) is also provided as an interrupt source (CTROVF).


The capture events are edge and sequencer qualified (i.e., ordered in time) by the polarity select and Mod4 gating, respectively.

One of these events can be selected as the interrupt source (from the eCAPx module) going to the PIE.

Seven interrupt events (CEVT1, CEVT2, CEVT3, CEVT4, CTR=PRD, CTR=CMP, CTR=OVF) can be generated. The interrupt enable register (ECEINT) is used to enable/disable individual interrupt event sources. The interrupt flag register (ECFLG) indicates if any interrupt event has been latched and contains the global interrupt flag bit (INT). An interrupt pulse is generated to the PIE only if any of the interrupt events are enabled, the flag bit is 1, and the INT flag bit is 0. The interrupt service routine must clear the global interrupt flag bit and the serviced event via the interrupt clear register (ECCLR) before any other interrupt pulses are generated. You can force an interrupt event via the interrupt force register (ECFRC). This is useful for test purposes.

Note: The CEVT1, CEVT2, CEVT3, CEVT4 flags are only active in capture mode (ECCTL2[CAP/APWM == 0]). The CTR=PRD, CTR=CMPEQ flags are only valid in APWM mode (ECCTL2[CAP/APWM == 1]). CNTOVF flag is valid in both modes.

Figure 7. Interrupts in eCAP Module



4.7 Shadow Load and Lockout Control

In capture mode, this logic inhibits (locks out) any shadow loading of CAP1 or CAP2 from APRD and ACMP registers, respectively.

In APWM mode, shadow loading is active and two choices are permitted:


- Immediate - APRD or ACMP are transferred to CAP1 or CAP2 immediately upon writing a new value.
- On period equal, i.e., CTR[31:0] = PRD[31:0]

4.8 APWM Mode Operation

Main operating highlights of the APWM section:

- The time-stamp counter bus is made available for comparison via 2 digital (32-bit) comparators.
- When CAP1/2 registers are not used in capture mode, their contents can be used as Period and Compare values in APWM mode.
- Double buffering is achieved via shadow registers APRD and ACMP (CAP3/4). The shadow register contents are transferred over to CAP1/2 registers either immediately upon a write, or on a CTR = PRD trigger.
- In APWM mode, writing to CAP1/CAP2 active registers will also write the same value to the corresponding shadow registers CAP3/CAP4. This emulates immediate mode. Writing to the shadow registers CAP3/CAP4 will invoke the shadow mode.
- During initialization, you must write to the active registers for both period and compare. This automatically copies the initial values into the shadow values. For subsequent compare updates, i.e., during run-time, you only need to use the shadow registers.

Figure 8. PWM Waveform Details Of APWM Mode Operation



The behavior of APWM active high mode (APWMPOL == 0) is as follows:


CMP = 0x00000000, output low for duration of period (0% duty)
 CMP = 0x00000001, output high 1 cycle
 CMP = 0x00000002, output high 2 cycles
 CMP = PERIOD, output high except for 1 cycle (<100% duty)
 CMP = PERIOD+1, output high for complete period (100% duty)
 CMP > PERIOD+1, output high for complete period

The behavior of APWM active low mode (APWMPOL == 1) is as follows:

CMP = 0x00000000, output high for duration of period (0% duty)
 CMP = 0x00000001, output low 1 cycle
 CMP = 0x00000002, output low 2 cycles
 CMP = PERIOD, output low except for 1 cycle (<100% duty)
 CMP = PERIOD+1, output low for complete period (100% duty)
 CMP > PERIOD+1, output low for complete period

5 Capture Module - Control and Status Registers

Figure 9. Time-Stamp Counter Register (TSCTR)




LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 1. Time-Stamp Counter Register (TSCTR) Field Descriptions

Bit(s)	Field	Description
31:0	TSCTR	Active 32-bit counter register that is used as the capture time-base

Figure 10. Counter Phase Control Register (CTRPHS)




LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 2. Counter Phase Control Register (CTRPHS) Field Descriptions

Bit(s)	Field	Description
31:0	CTRPHS	Counter phase value register that can be programmed for phase lag/lead. This register shadows TSCTR and is loaded into TSCTR upon either a SYNCI event or S/W force via a control bit. Used to achieve phase control synchronization with respect to other eCAP and EPWM time-bases.

Figure 11. Capture-1 Register (CAP1)




LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 3. Capture-1 Register (CAP1) Field Descriptions

Bit(s)	Field	Description
31:0	CAP1	This register can be loaded (written) by : Time-Stamp (i.e., counter value TSCTR) during a capture event) Software - may be useful for test purposes / initialization) APRD shadow register (i.e., CAP3) when used in APWM mode

Figure 12. Capture-2 Register (CAP2)



LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 4. Capture-2 Register (CAP2) Field Descriptions

Bit(s)	Field	Description
31:0	CAP2	This register can be loaded (written) by: <ul style="list-style-type: none"> Time-Stamp (i.e., counter value) during a capture event Software - may be useful for test purposes APRD shadow register (i.e., CAP4) when used in APWM mode

NOTE: In APWM mode, writing to CAP1/CAP2 active registers also writes the same value to the corresponding shadow registers CAP3/CAP4. This emulates immediate mode. Writing to the shadow registers CAP3/CAP4 invokes the shadow mode.

Figure 13. Capture-3 Register (CAP3)

31	0
CAP3	
R/W-0	

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 5. Capture-3 Register (CAP3) Field Descriptions

Bit(s)	Field	Description
31:0	CAP3	In CMP mode, this is a time-stamp capture register. In APWM mode, this is the period shadow (APRD) register. You update the PWM period value through this register. In this mode, CAP3 (APRD) shadows CAP1.

Figure 14. Capture-4 Register (CAP4)

31	0
CAP4	
R/W-0	

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 6. Capture-4 Register (CAP4) Field Descriptions

Bit(s)	Field	Description
31:0	CAP4	In CMP mode, this is a time-stamp capture register. In APWM mode, this is the compare shadow (ACMP) register. You update the PWM compare value via this register. In this mode, CAP4 (ACMP) shadows CAP2.

Figure 15. ECAP Control Register 1 (ECCTL1)

15	14	13	12	11	10	9	8
FREE/SOFT		PRESCALE					CAPLDEN
R/W-0		R/W-0					R/W-0
7	6	5	4	3	2	1	0
CTRRST4	CAP4POL	CTRRST3	CAP3POL	CTRRST2	CAP2POL	CTRRST1	CAP1POL
R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 7. ECAP Control Register 1 (ECCTL1) Field Descriptions

Bit(s)	Field	Value	Description
15:14	FREE/SOFT		Emulation Control
		00	TSCTR counter stops immediately on emulation suspend
		01	TSCTR counter runs until = 0
		1x	TSCTR counter is unaffected by emulation suspend (Run Free)
13:9	PRESCALE		Event Filter prescale select
		00000	Divide by 1 (i.e., no prescale, by-pass the prescaler)
		00001	Divide by 2
		00010	Divide by 4
		00011	Divide by 6
		00100	Divide by 8

Table 7. ECAP Control Register 1 (ECCTL1) Field Descriptions (continued)

Bit(s)	Field	Value	Description
		00101	Divide by 10
		...	
		11110	Divide by 60
		11111	Divide by 62
8	CAPLDEN		Enable Loading of CAP1-4 registers on a capture event
		0	Disable CAP1-4 register loads at capture event time.
		1	Enable CAP1-4 register loads at capture event time.
7	CTRRST4		Counter Reset on Capture Event 4
		0	<i>Do not</i> reset counter on Capture Event 4 (absolute time stamp operation)
		1	Reset counter after Capture Event 4 time-stamp has been captured (used in difference mode operation)
6	CAP4POL		Capture Event 4 Polarity select
		0	Capture Event 4 triggered on a rising edge (RE)
		1	Capture Event 4 triggered on a falling edge (FE)
5	CTRRST3		Counter Reset on Capture Event 3
		0	<i>Do not</i> reset counter on Capture Event 3 (absolute time stamp)
		1	Reset counter after Event 3 time-stamp has been captured (used in difference mode operation)
4	CAP3POL		Capture Event 3 Polarity select
		0	Capture Event 3 triggered on a rising edge (RE)
		1	Capture Event 3 triggered on a falling edge (FE)
3	CTRRST2		Counter Reset on Capture Event 2
		0	<i>Do not</i> reset counter on Capture Event 2 (absolute time stamp)
		1	Reset counter after Event 2 time-stamp has been captured (used in difference mode operation)
2	CAP2POL		Capture Event 2 Polarity select
		0	Capture Event 2 triggered on a rising edge (RE)
		1	Capture Event 2 triggered on a falling edge (FE)
1	CTRRST1		Counter Reset on Capture Event 1
		0	<i>Do not</i> reset counter on Capture Event 1 (absolute time stamp)
		1	Reset counter after Event 1 time-stamp has been captured (used in difference mode operation)
0	CAP1POL		Capture Event 1 Polarity select
		0	Capture Event 1 triggered on a rising edge (RE)
		1	Capture Event 1 triggered on a falling edge (FE)

Figure 16. ECAP Control Register 2 (ECCTL2)

15				11		10		9		8					
Reserved						APWMPOL		CAP/APWM		SWSYNC					
R-0						R/W-0		R/W-0		R/W-0					
7		6		5		4		3		2		1		0	
SYNCO_SEL				SYNCl_EN		TSCTRSTOP		REARM		STOP_WRAP				CONT/ONESH T	
R/W-0				R/W-0		R/W-0		R/W-0		R/W-1		R/W-1		R/W-0	

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 8. ECAP Control Register 2 (ECCTL2) Field Descriptions

Bit(s)	Field		Description
15:11	Reserved		Reserved
10	APWMPOL	0 1	APWM output polarity select. This is applicable only in APWM operating mode Output is active high (i.e., Compare value defines high time) Output is active low (i.e., Compare value defines low time)
9	CAP/APWM	0 1	CAP/APWM operating mode select 0 ECAP module operates in capture mode. This mode forces the following configuration: <ul style="list-style-type: none"> Inhibits TSCTR resets via CTR = PRD event Inhibits shadow loads on CAP1 and 2 registers Permits user to enable CAP1-4 register load CAPx/APWMx pin operates as a capture input 1 ECAP module operates in APWM mode. This mode forces the following configuration: <ul style="list-style-type: none"> Resets TSCTR on CTR = PRD event (period boundary) Permits shadow loading on CAP1 and 2 registers Disables loading of time-stamps into CAP1-4 registers CAPx/APWMx pin operates as a APWM output
8	SWSYNC	0 1	Software-forced Counter (TSCTR) Synchronizing. This provides a convenient software method to synchronize some or all ECAP time bases. In APWM mode, the synchronizing can also be done via the CTR = PRD event. 0 Writing a zero has no effect. Reading always returns a zero 1 Writing a one forces a TSCTR shadow load of current ECAP module and any ECAP modules down-stream providing the SYNCO_SEL bits are 0,0. After writing a 1, this bit returns to a zero. Note: Selection CTR = PRD is meaningful only in APWM mode; however, you can choose it in CAP mode if you find doing so useful.
7:6	SYNCO_SEL	00 01 10 11	Sync-Out Select 00 Select sync-in event to be the sync-out signal (pass through) 01 Select CTR = PRD event to be the sync-out signal 10 Disable sync out signal 11 Disable sync out signal
5	SYNCl_EN	0 1	Counter (TSCTR) Sync-In select mode 0 Disable sync-in option 1 Enable counter (TSCTR) to be loaded from CTRPHS register upon either a SYNCl signal or a S/W force event.
4	TSCTRSTOP	0 1	Time Stamp (TSCTR) Counter Stop (freeze) Control 0 TSCTR stopped 1 TSCTR free-running
3	RE-ARM	0 1	One-Shot Re-Arming Control, i.e. wait for stop trigger. Note: The re-arm function is valid in one shot or continuous mode. 0 Has no effect (reading always returns a 0) 1 Arms the one-shot sequence as follows: <ol style="list-style-type: none"> Resets the Mod4 counter to zero Unfreezes the Mod4 counter Enables capture register loads
2:1	STOP_WRAP	00 01	Stop value for one-shot mode. This is the number (between 1-4) of captures allowed to occur before the CAP(1-4) registers are frozen, i.e., capture sequence is stopped. Wrap value for continuous mode. This is the number (between 1-4) of the capture register in which the circular buffer wraps around and starts again. 00 Stop after Capture Event 1 in one-shot mode Wrap after Capture Event 1 in continuous mode. 01 Stop after Capture Event 2 in one-shot mode Wrap after Capture Event 2 in continuous mode.

Table 8. ECAP Control Register 2 (ECCTL2) Field Descriptions (continued)

Bit(s)	Field		Description
		10	Stop after Capture Event 3 in one-shot mode Wrap after Capture Event 3 in continuous mode.
		11	Stop after Capture Event 4 in one-shot mode Wrap after Capture Event 4 in continuous mode. Notes: STOP_WRAP is compared to Mod4 counter and, when equal, 2 actions occur: <ul style="list-style-type: none"> • Mod4 counter is stopped (frozen) • Capture register loads are inhibited In one-shot mode, further interrupt events are blocked until re-armed.
0	CONT/ONESHT	0	Continuous or one-shot mode control (applicable only in capture mode) Operate in continuous mode
		1	Operate in one-Shot mode

Figure 17. ECAP Interrupt Enable Register (ECEINT)

15							8								
Reserved															
7		6		5		4		3		2		1		0	
CTR=CMP		CTR=PRD		CTROVF		CEVT4		CEVT3		CEVT2		CETV1		Reserved	
R/W		R/W		R/W		R/W		R/W		R/W		R/W			

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 9. ECAP Interrupt Enable Register (ECEINT) Field Descriptions

Bits	Field	Value	Description
15:8	Reserved		
7	CTR=COMP	0 1	Counter Equal Compare Interrupt Enable Disable Compare Equal as an Interrupt source Enable Compare Equal as an Interrupt source
6	CTR=PRD	0 1	Counter Equal Period Interrupt Enable Disable Period Equal as an Interrupt source Enable Period Equal as an Interrupt source
5	CTROVF	0 1	Counter Overflow Interrupt Enable Disabled counter Overflow as an Interrupt source Enable counter Overflow as an Interrupt source
4	CEVT4	0 1	Capture Event 4 Interrupt Enable Disable Capture Event 4 as an Interrupt source Capture Event 4 Interrupt Enable
3	CEVT3	0 1	Capture Event 3 Interrupt Enable Disable Capture Event 3 as an Interrupt source Enable Capture Event 3 as an Interrupt source
2	CEVT2	0 1	Capture Event 2 Interrupt Enable Disable Capture Event 2 as an Interrupt source Enable Capture Event 2 as an Interrupt source
1	CEVT1	0 1	Capture Event 1 Interrupt Enable Disable Capture Event 1 as an Interrupt source Enable Capture Event 1 as an Interrupt source
0	Reserved		

The interrupt enable bits (CEVT1, ...) block any of the selected events from generating an interrupt. Events will still be latched into the flag bit (ECFLG register) and can be forced/cleared via the ECFRC/ECCLR registers.

The proper procedure for configuring peripheral modes and interrupts is as follows:

- Disable global interrupts
- Stop eCAP counter
- Disable eCAP interrupts
- Configure peripheral registers
- Clear spurious eCAP interrupt flags
- Enable eCAP interrupts
- Start eCAP counter
- Enable global interrupts

Figure 18. ECAP Interrupt Flag Register (ECFLG)

15															8																								
Reserved																																							
R-0																																							
7					6					5					4					3					2					1					0				
CTR=COMP					CTR=PRD					CTROVF					CEVT4					CETV3					CEVT2					CETV1					INT				
R-0					R-0					R-0					R-0					R-0					R-0					R-0					R-0				

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 10. ECAP Interrupt Flag Register (ECFLG) Field Descriptions

Bits	Field	Value	Description
15:8	Reserved		
7	CTR=COMP		Compare Equal Compare Status Flag. This flag is active only in APWM mode.
		0	Indicates no event occurred
		1	Indicates the counter (TSCTR) reached the compare register value (ACMP)
6	CTR=PRD		Counter Equal Period Status Flag. This flag is only active in APWM mode.
		0	Indicates no event occurred
		1	Indicates the counter (TSCTR) reached the period register value (APRD) and was reset.
5	CTROVF		Counter Overflow Status Flag. This flag is active in CAP and APWM mode.
		0	Indicates no event occurred.
		1	Indicates the counter (TSCTR) has made the transition from FFFFFFFF " 00000000
4	CEVT4		Capture Event 4 Status Flag This flag is only active in CAP mode.
		0	Indicates no event occurred
		1	Indicates the fourth event occurred at ECAPx pin
3	CEVT3		Capture Event 3 Status Flag. This flag is active only in CAP mode.
		0	Indicates no event occurred.
		1	Indicates the third event occurred at ECAPx pin.
2	CEVT2		Capture Event 2 Status Flag. This flag is only active in CAP mode.
		0	Indicates no event occurred.
		1	Indicates the second event occurred at ECAPx pin.
1	CEVT1		Capture Event 1 Status Flag. This flag is only active in CAP mode.
		0	Indicates no event occurred.
		1	Indicates the first event occurred at ECAPx pin.
0	INT		Global Interrupt Status Flag
		0	Indicates no interrupt generated.
		1	Indicates that an interrupt was generated.

Figure 19. ECAP Interrupt Clear Register (ECCLR)

15															8																								
Reserved																																							
R-0																																							
7					6					5					4					3					2					1					0				
CTR=COMP					CTR=PRD					CTROVF					CEVT4					CETV3					CETV2					CETV1					INT				
R/W-0					R/W-0					R/W-0					R/W-0					R/W-0					R/W-0					R/W-0					R/W-0				

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 11. ECAP Interrupt Clear Register (ECCLR) Field Descriptions

Bits	Field		Description
15:8	Reserved		
7	CTR=CMP		Counter Equal Compare Status Flag
		0	Writing a 0 has no effect. Always reads back a 0
		1	Writing a 1 clears the CTR=CMP flag condition
6	CTR=PRD		Counter Equal Period Status Flag
		0	Writing a 0 has no effect. Always reads back a 0
		1	Writing a 1 clears the CTR=PRD flag condition
5	CTROVF		Counter Overflow Status Flag
		0	Writing a 0 has no effect. Always reads back a 0
		1	Writing a 1 clears the CTROVF flag condition
4	CEVT4		Capture Event 4 Status Flag
		0	Writing a 0 has no effect. Always reads back a 0.
		1	Writing a 1 clears the CEVT4 flag condition.
3	CEVT3		Capture Event 3 Status Flag
		0	Writing a 0 has no effect. Always reads back a 0.
		1	Writing a 1 clears the CEVT3 flag condition.
2	CEVT2		Capture Event 2 Status Flag
		0	Writing a 0 has no effect. Always reads back a 0.
		0	Writing a 1 clears the CEVT2 flag condition.
1	CEVT1		Capture Event 1 Status Flag
		0	Writing a 0 has no effect. Always reads back a 0.
		1	Writing a 1 clears the CEVT1 flag condition.
0	INT		Global Interrupt Clear Flag
		0	Writing a 0 has no effect. Always reads back a 0.
		1	Writing a 1 clears the INT flag and enable further interrupts to be generated if any of the event flags are set to 1.

Figure 20. ECAP Interrupt Forcing Register (ECFRC)

15	14	13	12	11	10	9	8
Reserved							
R-0							
7	6	5	4	3	2	1	0
CTR=CMP	CTR=PRD	CTROVF	CEVT4	CEVT3	CEVT2	CEVT1	reserved
R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R/W-0	R-0

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset

Table 12. ECAP Interrupt Forcing Register (ECFRC) Field Descriptions

Bits	Field	Value	Description
15:8	Reserved	0	
7	CTR=CMP		Force Counter Equal Compare Interrupt
		0	No effect. Always reads back a 0.
		1	Writing a 1 sets the CTR=CMP flag bit.
6	CTR=PRD		Force Counter Equal Period Interrupt
		0	No effect. Always reads back a 0.
		1	Writing a 1 sets the CTR=PRD flag bit.
5	CTROVF		Force Counter Overflow
		0	No effect. Always reads back a 0.
		1	Writing a 1 to this bit sets the CTROVF flag bit.

Table 12. ECAP Interrupt Forcing Register (ECFRC) Field Descriptions (continued)

Bits	Field	Value	Description
4	CEVT4	0	Force Capture Event 4 No effect. Always reads back a 0.
		1	Writing a 1 sets the CEVT4 flag bit
3	CEVT3	0	Force Capture Event 3 No effect. Always reads back a 0.
		1	Writing a 1 sets the CEVT3 flag bit
2	CEVT2	0	Force Capture Event 2 No effect. Always reads back a 0.
		1	Writing a 1 sets the CEVT2 flag bit.
1	CEVT1	0	Force Capture Event 1 No effect. Always reads back a 0.
		0	Sets the CEVT1 flag bit.
0	reserved	0	

6 Register Mapping

Table 13 shows the eCAP module control and status register set.

Table 13. Control and Status Register Set

Name	Offset	Size (x16)	Description
Time Base Module Registers			
TSCTR	0x0000	2	Time-Stamp Counter
CTRPHS	0x0002	2	Counter Phase Offset Value Register
CAP1	0x0004	2	Capture 1 Register
CAP2	0x0006	2	Capture 2 Register
CAP3	0x0008	2	Capture 3 Register
CAP4	0x000A	2	Capture 4 Register
reserved	0x000C - 0x0013	8	
ECCTL1	0x0014	1	Capture Control Register 1
ECCTL2	0x0015	1	Capture Control Register 2
ECEINT	0x0016	1	Capture Interrupt Enable Register
ECFLG	0x0017	1	Capture Interrupt Flag Register
ECCLR	0x0018	1	Capture Interrupt Clear Register
ECFRC	0x0019	1	Capture Interrupt Force Register
Reserved	0x001A - 0x001F	6	

7 Application of the ECAP Module

The following sections will provide Applications examples and code snippets to show how to configure and operate the eCAP module. For clarity and ease of use, the examples use the eCAP “C” header files. Below are useful #defines which will help in the understanding of the examples.


```
// ECCTL1 ( ECAP Control Reg 1) //===== // CAPxPOL bits #define EC_RISING
0x0 #define EC_FALLING 0x1 // CTRRSTx bits #define EC_ABS_MODE 0x0 #define EC_DELTA_MODE 0x1 //
PRESCALE bits #define EC_BYPASS 0x0 #define EC_DIV1 0x0 #define EC_DIV2 0x1 #define EC_DIV4 0x2
#define EC_DIV6 0x3 #define EC_DIV8 0x4 #define EC_DIV10 0x5 // ECCTL2 ( ECAP Control Reg 2)
//===== // CONT/ONESHOT bit #define EC_CONTINUOUS 0x0 #define EC_ONESHOT 0x1
// STOPVALUE bit #define EC_EVENT1 0x0 #define EC_EVENT2 0x1 #define EC_EVENT3 0x2 #define
EC_EVENT4 0x3 // RE-ARM bit #define EC_ARM 0x1 // TSCTRSTOP bit #define EC_FREEZE 0x0 #define
EC_RUN 0x1 // SYNCO_SEL bit #define EC_SYNCIN 0x0 #define EC_CTR_PRD 0x1 #define EC_SYNCO_DIS 0x2
// CAP/APWM mode bit #define EC_CAP_MODE 0x0 #define EC_APWM_MODE 0x1 // APWMPOL bit #define
EC_ACTV_HI 0x0 #define EC_ACTV_LO 0x1 // Generic #define EC_DISABLE 0x0 #define EC_ENABLE 0x1
#define EC_FORCE 0x1
```


7.1 Example 1 - Absolute Time-Stamp Operation Rising Edge Trigger

Figure 21 shows an example of continuous capture operation (Mod4 counter wraps around). In this figure, TSCTR counts-up without resetting and capture events are qualified on the rising edge only, this gives period (and frequency) information.

On an event, the TSCTR contents (i.e., time-stamp) is first captured, then Mod4 counter is incremented to the next state. When the TSCTR reaches FFFFFFFF (i.e. maximum value), it wraps around to 00000000 (not shown in Figure 21), if this occurs, the CTROVF (counter overflow) flag is set, and an interrupt (if enabled) occurs, CTROVF (counter overflow) Flag is set, and an Interrupt (if enabled) occurs. Captured Time-stamps are valid at the point indicated by the diagram, i.e. after the 4th event, hence event CEVT4 can conveniently be used to trigger an interrupt and the CPU can read data from the CAPx registers.

Figure 21. Capture Sequence for Absolute Time-stamp and Rising Edge Detect




7.1.1 Code snippet for CAP mode Absolute Time, Rising Edge Trigger

```
// Code snippet for CAP mode Absolute Time, Rising edge trigger // Initialization Time
//===== // ECAP module 1 config ECAP1Regs.ECCTL1.bit.CAP1POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP2POL = EC_RISING; ECAP1Regs.ECCTL1.bit.CAP3POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP4POL = EC_RISING; ECAP1Regs.ECCTL1.bit.CTRRST1 = EC_ABS_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST2 = EC_ABS_MODE; ECAP1Regs.ECCTL1.bit.CTRRST3 = EC_ABS_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST4 = EC_ABS_MODE; ECAP1Regs.ECCTL1.bit.CAPLDEN = EC_ENABLE;
ECAP1Regs.ECCTL1.bit.PRESCALE = EC_DIV1; ECAP1Regs.ECCTL2.bit.CAP_APWM = EC_CAP_MODE;
ECAP1Regs.ECCTL2.bit.CONT_ONESHT = EC_CONTINUOUS; ECAP1Regs.ECCTL2.bit.SYNCO_SEL = EC_SYNCO_DIS;
ECAP1Regs.ECCTL2.bit.SYNCI_EN = EC_DISABLE; ECAP1Regs.ECCTL2.bit.TSCTRSTOP = EC_RUN; // Allow
TSCTR to run // Run Time ( e.g. CEVT4 triggered ISR call)
//===== TSt1 = ECAP1Regs.CAP1; // Fetch Time-Stamp captured
at t1 TSt2 = ECAP1Regs.CAP2; // Fetch Time-Stamp captured at t2 TSt3 = ECAP1Regs.CAP3; // Fetch
Time-Stamp captured at t3 TSt4 = ECAP1Regs.CAP4; // Fetch Time-Stamp captured at t4 Period1 =
TSt2-TSt1; // Calculate 1st period Period2 = TSt3-TSt2; // Calculate 2nd period Period3 = TSt4-
TSt3; // Calculate 3rd period
```

7.2 Example 2 - Absolute Time-Stamp Operation Rising and Falling Edge Trigger

In Figure 22 the eCAP operating mode is almost the same as in the previous section except capture events are qualified as either rising or falling edge, this now gives both period and duty cycle information, i.e: Period1 = $t_3 - t_1$, Period2 = $t_5 - t_3$, ...etc. Duty Cycle1 (on-time %) = $(t_2 - t_1) / \text{Period1} \times 100\%$, etc. Duty Cycle1 (off-time %) = $(t_3 - t_2) / \text{Period1} \times 100\%$, etc.

Figure 22. Capture Sequence for Absolute Time-stamp With Rising and Falling Edge Detect




7.2.1 Code snippet for CAP mode Absolute Time, Rising & Falling Edge Triggers

```
// Code snippet for CAP mode Absolute Time, Rising & Falling // edge triggers // Initialization
Time //===== // ECAP module 1 config ECAP1Regs.ECCTL1.bit.CAP1POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP2POL = EC_FALLING; ECAP1Regs.ECCTL1.bit.CAP3POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP4POL = EC_FALLING; ECAP1Regs.ECCTL1.bit.CTRRST1 = EC_ABS_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST2 = EC_ABS_MODE; ECAP1Regs.ECCTL1.bit.CTRRST3 = EC_ABS_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST4 = EC_ABS_MODE; ECAP1Regs.ECCTL1.bit.CAPLDEN = EC_ENABLE;
ECAP1Regs.ECCTL1.bit.PRESCALE = EC_DIV1; ECAP1Regs.ECCTL2.bit.CAP_APWM = EC_CAP_MODE;
ECAP1Regs.ECCTL2.bit.CONT_ONESHT = EC_CONTINUOUS; ECAP1Regs.ECCTL2.bit.SYNCO_SEL = EC_SYNCO_DIS;
ECAP1Regs.ECCTL2.bit.SYNCI_EN = EC_DISABLE; ECAP1Regs.ECCTL2.bit.TSCTRSTOP = EC_RUN; // Allow
TSCTR to run // Run Time ( e.g. CEVT4 triggered ISR call)
//===== TSt1 = ECAP1Regs.CAP1; // Fetch Time-Stamp captured
at t1 TSt2 = ECAP1Regs.CAP2; // Fetch Time-Stamp captured at t2 TSt3 = ECAP1Regs.CAP3; // Fetch
Time-Stamp captured at t3 TSt4 = ECAP1Regs.CAP4; // Fetch Time-Stamp captured at t4 Period1 =
TSt3-TSt1; // Calculate 1st period DutyOnTime1 = TSt2-TSt1; // Calculate On time DutyOffTime1 =
TSt3-TSt2; // Calculate Off time
```

7.3 Example 3 - Time Difference (Delta) Operation Rising Edge Trigger

This example Figure 23 shows how the eCAP module can be used to collect Delta timing data from pulse train waveforms. Here Continuous Capture mode (TSCTR counts-up without resetting, and Mod4 counter wraps around) is used. In Delta-time mode, TSCTR is Reset back to Zero on every valid event. Here Capture events are qualified as Rising edge only. On an event, TSCTR contents (i.e. Time-Stamp) is captured first, and then TSCTR is reset to Zero. The Mod4 counter then increments to the next state. If TSCTR reaches FFFFFFFF (i.e. Max value), before the next event, it wraps around to 00000000 and continues, a CINTOVF (counter overflow) Flag is set, and an Interrupt (if enabled) occurs. The advantage of Delta-time Mode is that the CAPx contents directly give timing data without the need for CPU calculations, i.e. $Period1 = T_1$, $Period2 = T_2$,...etc. As shown in the diagram, the CEVT1 event is a good trigger point to read the timing data, T_1 , T_2 , T_3 , T_4 are all valid here.

Figure 23. Capture Sequence for Delta Mode Time-stamp and Rising Edge Detect




7.3.1 Code snippet for CAP mode Delta Time, Rising Edge Trigger

```
// Code snippet for CAP mode Delta Time, Rising edge trigger // Initialization Time
//===== // ECAP module 1 config ECAP1Regs.ECCTL1.bit.CAP1POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP2POL = EC_RISING; ECAP1Regs.ECCTL1.bit.CAP3POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP4POL = EC_RISING; ECAP1Regs.ECCTL1.bit.CTRRST1 = EC_DELTA_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST2 = EC_DELTA_MODE; ECAP1Regs.ECCTL1.bit.CTRRST3 = EC_DELTA_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST4 = EC_DELTA_MODE; ECAP1Regs.ECCTL1.bit.CAPLDEN = EC_ENABLE;
ECAP1Regs.ECCTL1.bit.PRESCALE = EC_DIV1; ECAP1Regs.ECCTL2.bit.CAP_APWM = EC_CAP_MODE;
ECAP1Regs.ECCTL2.bit.CONT_ONESHT = EC_CONTINUOUS; ECAP1Regs.ECCTL2.bit.SYNCO_SEL = EC_SYNCO_DIS;
ECAP1Regs.ECCTL2.bit.SYNCI_EN = EC_DISABLE; ECAP1Regs.ECCTL2.bit.TSCTRSTOP = EC_RUN; // Allow
TSCTR to run // Run Time ( e.g. CEVT1 triggered ISR call)
//===== // Note: here Time-stamp directly represents the
Period value. Period4 = ECAP1Regs.CAP1; // Fetch Time-Stamp captured at T1 Period1 =
ECAP1Regs.CAP2; // Fetch Time-Stamp captured at T2 Period2 = ECAP1Regs.CAP3; // Fetch Time-Stamp
captured at T3 Period3 = ECAP1Regs.CAP4; // Fetch Time-Stamp captured at T4
```

7.4 Example 4 - Time Difference (Delta) Operation Rising and Falling Edge Trigger

In Figure 24 the eCAP operating mode is almost the same as in previous section except Capture events are qualified as either Rising or Falling edge, this now gives both Period and Duty cycle information, i.e: Period1 = $T_1 + T_2$, Period2 = $T_3 + T_4$, ...etc Duty Cycle1 (on-time %) = $T_1 / \text{Period1} \times 100\%$, etc Duty Cycle1 (off-time %) = $T_2 / \text{Period1} \times 100\%$, etc

Figure 24. Capture Sequence for Delta Mode Time-stamp With Rising and Falling Edge Detect



During initialization, you must write to the active registers for both period and compare. This will then automatically copy the init values into the shadow values. For subsequent compare updates, i.e. during run-time, only the shadow registers must be used.

7.4.1 Code snippet for CAP mode Delta Time, Rising and Falling Edge Triggers


```
// Code snippet for CAP mode Delta Time, Rising and Falling // edge triggers // Initialization
Time //===== // ECAP module 1 config ECAP1Regs.ECCTL1.bit.CAP1POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP2POL = EC_FALLING; ECAP1Regs.ECCTL1.bit.CAP3POL = EC_RISING;
ECAP1Regs.ECCTL1.bit.CAP4POL = EC_FALLING; ECAP1Regs.ECCTL1.bit.CTRRST1 = EC_DELTA_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST2 = EC_DELTA_MODE; ECAP1Regs.ECCTL1.bit.CTRRST3 = EC_DELTA_MODE;
ECAP1Regs.ECCTL1.bit.CTRRST4 = EC_DELTA_MODE; ECAP1Regs.ECCTL1.bit.CAPLDEN = EC_ENABLE;
ECAP1Regs.ECCTL1.bit.PRESCALE = EC_DIV1; ECAP1Regs.ECCTL2.bit.CAP_APWM = EC_CAP_MODE;
ECAP1Regs.ECCTL2.bit.CONT_ONESHT = EC_CONTINUOUS; ECAP1Regs.ECCTL2.bit.SYNCO_SEL = EC_SYNCO_DIS;
ECAP1Regs.ECCTL2.bit.SYNCI_EN = EC_DISABLE; ECAP1Regs.ECCTL2.bit.TSCTRSTOP = EC_RUN; // Allow
TSCTR to run // Run Time ( e.g. CEVT1 triggered ISR call)
//===== // Note: here Time-stamp directly represents the
Duty cycle values. DutyOnTime1 = ECAP1Regs.CAP2; // Fetch Time-Stamp captured at T2 DutyOffTime1
= ECAP1Regs.CAP3; // Fetch Time-Stamp captured at T3 DutyOnTime2 = ECAP1Regs.CAP4; // Fetch Time-
Stamp captured at T4 DutyOffTime2 = ECAP1Regs.CAP1; // Fetch Time-Stamp captured at T1 Period1 =
DutyOnTime1 + DutyOffTime1; Period2 = DutyOnTime2 + DutyOffTime2;
```


8 Application of the APWM Mode

In this example, the eCAP module is configured to operate as a PWM generator. Here a very simple single channel PWM waveform is generated from output pin APWMx. The PWM polarity is active high, which means that the compare value (CAP2 reg is now a compare register) represents the on-time (high level) of the period. Alternatively, if the APWMPOL bit is configured for active low, then the compare value represents the off-time. Note here values are in hexadecimal ("h") notation.

8.1 Example 1 - Simple PWM Generation (Independent Channel/s)

Figure 25. PWM Waveform Details of APWM Mode Operation



Example 1. Code Snippet for APWM Mode

```
// Code snippet for APWM mode Example 1 // Initialization Time //===== // ECAP
module 1 config ECAP1Regs.CAP1 = 0x1000; // Set period value ECAP1Regs.CTRPHS = 0x0; // make phase
zero ECAP1Regs.ECCTL2.bit.CAP_APWM = EC_APWM_MODE; ECAP1Regs.ECCTL2.bit.APWMPOL = EC_ACTV_HI; //
Active high ECAP1Regs.ECCTL2.bit.SYNCI_EN = EC_DISABLE; // Synch not used
ECAP1Regs.ECCTL2.bit.SYNCO_SEL = EC_SYNCO_DIS; // Synch not used ECAP1Regs.ECCTL2.bit.TSCTRSTOP =
EC_RUN; // Allow TSCTR to run // Run Time (Instant 1, e.g. ISR call) //=====
ECAP1Regs.CAP2 = 0x300; // Set Duty cycle i.e. compare value // Run Time (Instant 2, e.g. another ISR
call) //===== ECAP1Regs.CAP2 = 0x500; // Set Duty cycle i.e. compare value
```

Appendix A Revision History

The following technical change(s) were made to this document.

Table 14. Changes Made in This Revision

Location	Additions, Deletions, Changes
Global	Added the 2803x device.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
RF/IF and ZigBee® Solutions	www.ti.com/lprf

Applications

Audio	www.ti.com/audio
Automotive	www.ti.com/automotive
Broadband	www.ti.com/broadband
Digital Control	www.ti.com/digitalcontrol
Medical	www.ti.com/medical
Military	www.ti.com/military
Optical Networking	www.ti.com/opticalnetwork
Security	www.ti.com/security
Telephony	www.ti.com/telephony
Video & Imaging	www.ti.com/video
Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2009, Texas Instruments Incorporated